

QD4747 Series

CN1 **CN2 side**

CN1 = DF9-31S-1V (molded) CN2 Side = 32 Conductor .5mm FFC

1
2
3
4
5
6
7
8
9
10
11
12
13
14
15
16
17
18
19
20
21
22
23
24
25
26
27
28
29
30
31
NC

1
2
3
4
5
6
7
8
9
10
11
12
13
14
15
16
17
18
19
20
21
22
23
24
25
26
27
28
29
30
31
32

← **Extends under mold
& is cut blunt (NC).**

Note: FFC cable must have 32 conductors to allow termination to a 32 position FFC connector on CN2 side. Conductor #32 extends under molded section & is cut (no connection).

Part No.	Description	Length "L" (mm)
QD4747-3	DF9-31S-1-.5FFC(32)-76	76
QD4747-6	DF9-31S-1-.5FFC(32)-153	153
QD4747-9	DF9-31S-1-.5FFC(32)-229	229
QD4747-10	DF9-31S-1-.5FFC(32)-254	254
QD4747-11	DF9-31S-1-.5FFC(32)-280	280
QD4747-12	DF9-31S-1-.5FFC(32)-305	305

